

Solution : Mise en équations d'un GRAFCET

Etape	Activation	Désactivation
X1	X5.S3 + X8 .X10	X2 + X6.X9
X2	X1 . S1 . S8 + X5 . $\bar{S3}$. S10	X3 + X5
X3	X2 . S3 . S4	X4
X4	X3 . S2	X5
X5	X4 . B9 + X2 . $\bar{S4}$	X1 + X2
X6	X1 . $\bar{S1}$. S8	X7
X7	X6 . S2	X8
X8	X7 . B5	X1
X9	X1 . $\bar{S1}$. S8	X10
X10	X9 . S6	X1

Sorties	Equations
KM2	X5
KM5	X3 . B5 + X6
KM6	X2 + X9
Y2	X7
Y3	X4